

# PS1-5-1-65



## General Information

<b>Extended Product Type:</b>	PS1-5-1-65
<b>Product ID:</b>	1SAM201906R1115
<b>EAN:</b>	4013614400759
<b>Catalog Description:</b>	PS1-5-1-65 3-Phase Busbar
<b>Long Description:</b>	PS1-5-1-65 3-phase busbar for 5 MS116 / MS132 with 1 HK/SK, I <sub>e</sub> =65A

## Categories

Products » Low Voltage Products and Systems » Control Products » Manual Motor Starters » Manual Motor Starters Accessories

## Ordering

<b>EAN:</b>	4013614400759
<b>Minimum Order Quantity:</b>	1 piece
<b>Customs Tariff Number:</b>	85369085

## Container Information

<b>Package Level 1 Width:</b>	80.0 mm
<b>Package Level 1 Length:</b>	264.0 mm
<b>Package Level 1 Height:</b>	46.0 mm
<b>Package Level 1 Gross Weight:</b>	1.130 kg
<b>Package Level 1 EAN:</b>	4013614488139
<b>Package Level 1 Units:</b>	10 piece

## Dimensions

<b>Product Net Width:</b>	257.5 mm
<b>Product Net Height:</b>	32.3 mm
<b>Product Net Depth:</b>	13.0 mm
<b>Product Net Weight:</b>	0.108 kg

## Technical

<b>Rated Operational Voltage:</b>	690 V
<b>Rated Operational Current (I<sub>e</sub>):</b>	65 A
<b>Degree of Protection:</b>	IP20
<b>Standards:</b>	IEC/EN 60947-1 IEC/EN 60947-4-1 UL 60947-1 UL 60947-4-1
<b>Product Name:</b>	3-Phase Busbar
<b>Suitable For:</b>	MS116 MS132
<b>Suitable for Product Class:</b>	Manual Motor Starters

## Environmental

<b>Ambient Air Temperature:</b>	Operation -25 .... +70 °C Storage -50 ...+80 °C
<b>RoHS Status:</b>	Following EU Directive 2002/95/EC August 18, 2005 and amendment

## Technical UL/CSA

<b>Maximum Operating Voltage</b>	Main Circuit 600 V
<b>UL/CSA:</b>	
<b>Ampere Rating UL/CSA:</b>	65 A

---

### Certificates and Declarations (Document Number)

---

<b>cUL Certificate:</b>	1SAA963001-1701
<b>Declaration of Conformity - CE:</b>	1SAD938509-0056
<b>GOST Certificate:</b>	1SAA937000-2703
<b>RoHS Information:</b>	1SAA963003-4402
<b>UL Certificate:</b>	1SAA963001-1602

---

### Classifications

---

<b>E-nummer:</b>	3111682
<b>Object Classification Code:</b>	W
<b>UNSPSC:</b>	39121100

---

